

FieldCast



Datasheet FieldCast Converter Three

- two channel converter: SDI to fiber / fiber to SDI
- data rate: 270Mb/s to 12Gb/s
- auto selection to input data rate
- compliant to all SD, HD, 2K, UltraHD and DCI 4K standards
- SDI video sampling: 4:2:2 and 4:4:4
- SDI color space: 4:2:2 and 4:4:4
- SDI audio sampling: 44kHz and 48kHz, 24bit
- SDI in to fiber out: one input with reclocked loopthrough output
- SDI out from fiber in: double output
- fiber in sensitivity: 3G better than -20dBm, 12G better than -13dBm
- fiber transmit wavelength: 1310 nm
- fiber out power: 3G -8 to -3 dBm, 12G -3 to 0 dBm;
- fiber receive wavelength: 1290 nm to 1610 nm.
- led indication: valid power input, SDI input, fiber input, data rate (3G, 6G or 12G)
- SDI connector: 4x 75ohm BNC connector for SDI in, SDI loopthrough and 2x SDI out
- fiber connector: compact 2Core single mode for fiber in, fiber out, screw on type
- power input: 12VDC nominal voltage
- power input connector: cylindrical 5.5 mm., screw on type
- power input connector cable: XLR 4-pin male to cylindrical 5.5 mm. screw on type, 2 m.
- power supply: 110-240VAc to 12VDC 10000mA with XLR 4-pin female connector
- power consumption: < 3W
- stainless steel 14"-20 mounting plate

the fiber optic system

Hazepad 43, 1544 PW, Zaandijk, The Netherlands
+31 (0)75 6572290 | www.fieldcast.eu | info@fieldcast.eu